RCT OFF-GRID INVERTER

RCT AXPERT MAX II TWIN 8K

RCT

RCT

. 1851, 1985, 1985, 1985

- Dual outputs, for smart load management
- Maximum PV input current increases to 27A
- Wide PV input voltage range 90 VDC \sim 450 VDC
- Status indication with RGB lights
- Built-in Wi-Fi for mobile monitoring (Android / iOS App is available)
- Supports USB on-the-go function
- Reserved communication port for BMS (RS485, CAN-BUS or RS232)
- Replaceable fan design for ease of maintenance
- Battery independent design
- Configurable AC / PV output usage timer and prioritization
- Compatible to Utility Mains or generator input
- Built-in anti-dust kit
- Built-in DC output for DC fan, LED bulb, router and so on
- Parallel operation with 6 units

RATED POWER

PARALLEL CAPABILITY Yes, 6 Units

8000 VA / 8000 W

VOLTAGE: 230 VAC

INPUT

DUTPUT

SELECTED VOLTAGE RANGE:

170 - 280 VAC (For Personal Computers) 90 - 280 VAC (For Home Appliances)

FREQUENCY RANGE:

50 Hz / 60 Hz (Auto sensing)

AC VOLTAGE REGULATION (Batt. mode): 230 VAC ± 5%

SURGE POWER: 16000 VA

EFFICIENCY (PEAK): 93%

TRANSFER TIME: 10ms (For Personal Computers) 20ms (For Home Appliances)

WAVEFORM:

Pure sine wave

DC VOLTAGE: 12 VDC ± 5%, 100W



BATTERY

BATTERY VOLTAGE: 48 VDC

FLOATING CHARGE VOLTAGE: 54 VDC

OVERCHARGE PROTECTION: 66 VDC

SOLAR CHARGER TYPE: MPPT

MAXIMUM PV ARRAY POWER: 8000 W (4000 W x2)

MPPT RANGE @ OPERATING VOLTAGE: 90 ~ 450 VDC

MAXIMUM PV ARRAY OPEN CIRCUIT VOLTAGE: 500 VDC

MAXIMUM PV INPUT CURRENT: 27 A x2 (Max. 40 A)

MAXIMUM SOLAR CHARGE CURRENT: 150 A

MAXIMUM AC CHARGE CURRENT: 120 A

MAXIMUM CHARGE CURRENT: 150 A

COMMUNICATION INTERFACE: USB / RS232 / RS485 / Wi-Fi / Dry-contact

HUMIDITY:

5% to 95% Relative Humidity (Non-condensing)

OPERATING TEMPERATURE: -10°C to 50°C

STORAGE TEMPERATURE: -15°C to 60°C

Compliance Safety: CE

Please Note: Product specifications are subject to change without further notice.

PRODUCT DIMENSIONS & WEIGHT: 158.4 x 503.6 x 530.8 mm & 20 (kgs)

WWW.RCTZONE.CO.ZA

SOLAR CHARGER & AC CHARGER

ENVIRONMENT

RCT OFF-GRID INVERTER

RCT AXPERT MAX II TWIN 11K

RCT

RCT

. 1851, 1985, 1985, 1985

- Dual outputs, for smart load management
- Maximum PV input current increases to 27A
- Wide PV input voltage range 90 VDC ~ 450 VDC
- Status indication with RGB lights
- Built-in Wi-Fi for mobile monitoring (Android / iOS App is available)
- Supports USB on-the-go function
- Reserved communication port for BMS (RS485, CAN-BUS or RS232)
- Replaceable fan design for ease of maintenance
- Battery independent design
- Configurable AC / PV output usage timer and prioritization
- Compatible to Utility Mains or generator input
- Built-in anti-dust kit

230 VAC

- Built-in DC output for DC fan, LED bulb, router and so on
- Parallel operation with 6 units

RATED POWER

PARALLEL CAPABILITY Yes, 6 Units

11000 VA / 11000 W

VOLTAGE:

INPUT

DUTPUT

SELECTED VOLTAGE RANGE:

170 - 280 VAC (For Personal Computers) 90 - 280 VAC (For Home Appliances)

FREQUENCY RANGE:

50 Hz / 60 Hz (Auto sensing)

AC VOLTAGE REGULATION (Batt. mode): 230 VAC ± 5%

SURGE POWER: 22000 VA

EFFICIENCY (PEAK): 93%

TRANSFER TIME: 10ms (For Personal Computers) 20ms (For Home Appliances)

WAVEFORM:

Pure sine wave

DC VOLTAGE: 12 VDC ± 5%, 100W



BATTERY

48 VDC

BATTERY VOLTAGE:

FLOATING CHARGE VOLTAGE: 54 VDC

OVERCHARGE PROTECTION: 63 VDC

SOLAR CHARGER TYPE: MPPT

MAXIMUM PV ARRAY POWER: 11000 W (5500 W x2)

MPPT RANGE @ OPERATING VOLTAGE: 90 ~ 450 VDC

MAXIMUM PV ARRAY OPEN CIRCUIT VOLTAGE: 500 VDC

MAXIMUM PV INPUT CURRENT: 27 A x2 (Max. 40 A)

MAXIMUM SOLAR CHARGE CURRENT: 150 A

MAXIMUM AC CHARGE CURRENT: 150 A

MAXIMUM CHARGE CURRENT: 150 A

COMMUNICATION INTERFACE: USB / RS232 / RS485 / Wi-Fi / Dry-contact

HUMIDITY:

5% to 95% Relative Humidity (Non-condensing)

OPERATING TEMPERATURE: -10°C to 50°C

STORAGE TEMPERATURE: -15°C to 60°C

Compliance Safety: CE

Please Note: Product specifications are subject to change without further notice.

PRODUCT DIMENSIONS & WEIGHT: 158.4 x 503.6 x 530.8 mm & 20 (kgs)

WWW.RCTZONE.CO.ZA

SOLAR CHARGER & AC CHARGER

ENVIRONMENT